



## Axion Kiosk App Launcher ELAN Driver

### Overview

This driver integrates the Axion Kiosk Software to the Axion Touchpanel into the ELAN project. It is recommended to set the touchpanel to a static ip or assign a DHCP reservation.

### Features

- Kiosk Text To Speech – Announces a text message.
- Kiosk Mode– Lock or unlock the Kiosk
- Kiosk Message Overlay – Show message in an overlay. NOTE: Will stay forever until you send a blank one
- Kiosk Screen– Set the Kiosk screen mode to off, on, or force sleep mode.
- Kiosk Simulate Motion– Simulates motion on the Kiosk.
- Kiosk Screensaver – Start and stop Axion Kiosk App Screensaver or Android Screen Saver (Daydream)

### Quick Start Guide

- Add the touchpanel driver to project in the Inputs/Outputs tab of Configurator.
  - Enter the IP address of the touchpanel.
  - Enter the API port of the touchpanel. Default is 2424 unless otherwise configured.
  - Enter Kiosk Password in the password property field.
  - Enter custom messages to use with text to speech or message overlay commands.

**Note that the driver status will only turn green after the first successful command is sent from the driver.**

### Control

- Using the event mapper or any other aspect of ELAN that allows the use of registered commands, select the command/action for a given condition. When that condition is met, the

command will execute on the driver and perform the appropriate actions on the device.

## **Change Log**

### **Version 1**

- Initial Release